

## IR Remote Controller Code Conversion Table for DLA-G150CL Series

Button	Code
↑	01H
↓	02H
EXIT	03H
PRESET	04H
FREEZE	0FH
QUICK ALIGN	13H
OPERATE	17H
V-KEYSTONE(+)	1BH
V-KEYSTONE(-)	1CH
HIDE	1DH
ZOOM (T)	23H
ZOOM (W)	24H
DIGITAL ZOOM(+)	2AH
DIGITAL ZOOM(-)	2BH
MENU	2EH
ENTER	2FH
→	34H
←	36H
FOCUS (+)	3CH
FOCUS (-)	3DH
PC1	46H
PC2	47H
DVI	48H
VIDEO	4BH
Y/C	4CH
COMP	4DH
SCREEN (W)	56H
SCREEN (S)	57H