

## I/R Remote Control Code Listing



<b>Model Number</b>	DLA-HX2U
---------------------	----------

Button / Function	Code	Comment
↑	01H	
↓	02H	
EXIT	03H	
PRESET	04H	
POWER ON	05H	
POWER OFF	06H	
FREEZE	0FH	
PC	10H	
VIDEO	11H	
QUICK ALIGH	13H	
OPERATE	17H	
V-KEYSTONE +	1BH	
V-KEYSTONE -	1CH	
HIDE	1DH	
VOLUME +	1EH	
VOLUME -	1FH	
DIGITAL ZOOM +	2AH	
DIGITAL ZOOM -	2BH	
MENU	2EH	
ENTER	2FH	
→	34H	
←	36H	
H-KEYSTONE +	40H	
H-KEYSTONE -	41H	
PC1	46H	
PC2	47H	
DVI	48H	
VIDEO	4BH	
Y/C	4CH	
COMPONENT	4DH	