

I/R Remote Control Code Listing



Model Number	LD-HD2KB
---------------------	----------

Function	Decimal Code	Hex Code	BIN Code					
			D5	D4	D3	D2	D1	D0
Power On	1	1	0	0	0	0	0	1
Power Off	2	2	0	0	0	0	1	0
Video	3	3	0	0	0	0	1	1
S-Video	4	4	0	0	0	1	0	0
RGB	5	5	0	0	0	1	0	1
YPrPb	6	6	0	0	0	1	1	0
Pass thru	7	7	0	0	0	1	1	1
Pass thru Xcode	8	8	0	0	1	0	0	0
4:3	9	9	0	0	1	0	0	1
Letterbox	10	0a	0	0	1	0	1	0
Anamorphic	11	0b	0	0	1	0	1	1
Brightness	12	0c	0	0	1	1	0	0
Contrast	13	0d	0	0	1	1	0	1
Color	14	0e	0	0	1	1	1	0
Tint	15	0f	0	0	1	1	1	1
Detail	16	10	0	1	0	0	0	0
Menu	17	11	0	1	0	0	0	1
Preset	18	12	0	1	0	0	1	0
Store	19	13	0	1	0	0	1	1
Function Up	20	14	0	1	0	1	0	0
Function Down	21	15	0	1	0	1	0	1
Value Up	22	16	0	1	0	1	1	0
Value Down	23	17	0	1	0	1	1	1
0	24	18	0	1	1	0	0	0
1	25	19	0	1	1	0	0	1
2	26	1a	0	1	1	0	1	0
3	27	1b	0	1	1	0	1	1
4	28	1c	0	1	1	1	0	0
5	29	1d	0	1	1	1	0	1
6	30	1e	0	1	1	1	1	0
7	31	1f	0	1	1	1	1	1
8	32	20	1	0	0	0	0	0
9	33	21	1	0	0	0	0	1

I/R Custom Address Code

Address	Decimal Code	Hex Code	Bin Code				
			C4	C3	C2	C1	C0
Default	27	1b	1	1	0	1	1

V1.031306