

## IR Remote Controller Code Conversion Table for DLA-QX1 Series

Button	Code
↑	01H
↓	02H
EXIT	03H
OPERATE	17H
KEYSTONE(+)	1BH
KEYSTONE(-)	1CH
HIDE	1DH
SHIFT(+)	21H
SHIFT(-)	22H
ZOOM (T)	23H
ZOOM (W)	24H
DIGITAL ZOOM(+)	2AH
DIGITAL ZOOM(-)	2BH
SHUTTER(ON)	2CH
SHUTTER(OFF)	2DH
MENU	2EH
ENTER	2FH
→	34H
←	36H
FOCUS (+)	3CH
FOCUS (-)	3DH
VIC1	50H
VIC2	51H
VIC3	52H